

Eaton 110939

Eaton Moeller® series M22 Emergency stop/emergency switching off pushbutton, RMQ-Titan, Blister pack for hanging

PRODUCT NAME	Eaton Moeller® series M22 Emergency stop/emergency switching off pushbutton
CATALOG NUMBER	110939
PRODUCT LENGTH/DEPTH	70 mm
PRODUCT HEIGHT	105 mm
PRODUCT WIDTH	70 mm
PRODUCT WEIGHT	0.22 kg
CERTIFICATIONS	CE

10.10 TEMPERATURE RISE	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 SHORT-CIRCUIT RATING	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 ELECTROMAGNETIC COMPATIBILITY	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 MECHANICAL FUNCTION	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.
10.2.2 CORROSION RESISTANCE	Meets the product standard's requirements.
10.2.3.1 VERIFICATION OF THERMAL STABILITY OF ENCLOSURES	Meets the product standard's requirements.
10.2.3.2 VERIFICATION OF RESISTANCE OF INSULATING MATERIALS TO NORMAL HEAT	Meets the product standard's requirements.
10.2.3.3 RESIST. OF INSUL. MAT. TO ABNORMAL HEAT/FIRE BY INTERNAL ELECT. EFFECTS	Meets the product standard's requirements.
10.2.4 RESISTANCE TO ULTRA-VIOLET (UV) RADIATION	Please enquire
10.2.5 LIFTING	Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 MECHANICAL IMPACT	Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 INSCRIPTIONS	Meets the product standard's requirements.
10.3 DEGREE OF PROTECTION OF ASSEMBLIES	Does not apply, since the entire switchgear needs to be evaluated.

/	IL04716005Z.pdf
	IL04716002Z
	RMQ small E-Stop emergency-stop button

10.4 CLEARANCES AND CREEPAGE DISTANCES	Meets the product standard's requirements.
10.5 PROTECTION AGAINST ELECTRIC SHOCK	Does not apply, since the entire switchgear needs to be evaluated.
10.6 INCORPORATION OF SWITCHING DEVICES AND COMPONENTS	Does not apply, since the entire switchgear needs to be evaluated.
10.7 INTERNAL ELECTRICAL CIRCUITS AND CONNECTIONS	Is the panel builder's responsibility.
10.8 CONNECTIONS FOR EXTERNAL CONDUCTORS	Is the panel builder's responsibility.
10.9.2 POWER-FREQUENCY ELECTRIC STRENGTH	Is the panel builder's responsibility.
10.9.3 IMPULSE WITHSTAND VOLTAGE	Is the panel builder's responsibility.
10.9.4 TESTING OF ENCLOSURES MADE OF INSULATING MATERIAL	Is the panel builder's responsibility.
CONNECTION TO SMARTWIRE-DT	No
ENCLOSURE MATERIAL	Plastic
NUMBER OF BUTTONS (MUSHROOM SHAPE)	1
NUMBER OF COMMAND POSITIONS	1
NUMBER OF CONTACTS (CHANGE-OVER CONTACTS)	0
NUMBER OF CONTACTS (NORMALLY CLOSED CONTACTS)	1
NUMBER OF CONTACTS (NORMALLY OPEN CONTACTS)	0
NUMBER OF KEY SWITCHES	0
NUMBER OF PILOT LIGHTS	0
NUMBER OF PUSHBUTTONS	0
ENCLOSURE COLOR	Yellow
NUMBER OF SWITCHES (SELECTOR)	0
RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 50	500 V

HZ - MAX	
RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 50 HZ - MIN	115 V
RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 60 HZ - MAX	500 V
RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 60 HZ - MIN	115 V
RATED CONTROL SUPPLY VOLTAGE (US) AT DC - MAX	220 V
RATED CONTROL SUPPLY VOLTAGE (US) AT DC - MIN	24 V
MOUNTING METHOD	Surface mounting
DEGREE OF PROTECTION	IP Other NEMA 4X, 13
SUITABLE FOR	Emergency stop

PROJECT NAME:
PROJECT NUMBER:
PREPARED BY:
:



Eaton House
30 Pembroke Road
Dublin 4,
Eaton.com

© 2025

Follow us on social media to get the latest product and support information.

