## Eaton 198521

Eaton Moeller® series Rapid Link DOL starter, 6.6 A, Sensor input 2, 230/277 V AC, AS-Interface®, S-7.A.E. for 62 modules, HAN Q5

PRODUCT NAME	Eaton Rapid Link DOL starter
CATALOG NUMBER	198521
PRODUCT LENGTH/DEPTH	120 mm
PRODUCT HEIGHT	270 mm
PRODUCT WIDTH	220 mm
PRODUCT WEIGHT	1.63 kg
CERTIFICATIONS	RoHS CE UL 60947-4-2 IEC/EN 60947-4-2 CCC UL approval UL 60947-4-2
CATALOG NOTES	Assigned motor rating: for normal internally and externally ventilated 4 pole, three-phase asynchronous motors with 1500 rpm at 50 Hz or 1800 min at 60 Hz



ТҮРЕ	DOL starter
FEATURES	Parameterization: drivesConnect mobile (App) Diagnostics and reset on device and via AS-Interface Parameterization: Fieldbus Parameterization: drivesConnect Parameterization: Keypad
10.10 TEMPERATURE RISE	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 SHORT-CIRCUIT RATING	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 ELECTROMAGNETIC COMPATIBILITY	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 MECHANICAL FUNCTION	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.
10.2.2 CORROSION RESISTANCE	Meets the product standard's requirements.
10.2.3.1 VERIFICATION OF THERMAL STABILITY OF ENCLOSURES	Meets the product standard's requirements.
10.2.3.2 VERIFICATION OF RESISTANCE OF INSULATING MATERIALS TO NORMAL HEAT	Meets the product standard's requirements.
10.2.3.3 RESIST. OF INSUL. MAT. TO ABNORMAL HEAT/FIRE BY INTERNAL ELECT. EFFECTS	Meets the product standard's requirements.
10.2.4 RESISTANCE TO ULTRA-VIOLET (UV) RADIATION	Meets the product standard's requirements.

DECLARATIONS OF	DA-DC-00003964.pdf
CONFORMITY	DA-DC-00004184.pdf
ECAD MODEL	ETN.RAMO5-D202A32-
	<u>5120S1.edz</u>
MCAD MODEL	ramo5_v1.dwg
WICAD WIODEL	ramo5 v1.stp
	<u>IL034084ZU</u>
	eaton-rapid-link-5- brochure-br040014en-en- us.pdf
	eaton-powerxl-variable- frequency-drives-material- handling-brochure- br040017en-en-us.pdf
	eaton-rapid-link-5- mn034004en-us.pdf
	eaton-bus-adapter- rapidlink-reversing-starter- dimensions.eps
	eaton-bus-adapter- rapidlink-reversing-starter- dimensions-002.eps

10.2.5 LIFTING  Does not apply, since the entire switchgear needs to be evaluated.  10.2.6 MECHANICAL IMPACT  10.2.7 INSCRIPTIONS  Meets the product standard's requirements.  10.3 DEGREE OF PROTECTION OF ASSEMBLIES  10.4 CLEARANCES AND CREEPAGE DISTANCES  10.5 PROTECTION DOES not apply, since the entire switchgear needs to be evaluated.  10.6 INCORPORATION OF SWITCHING DEVICES AND COMPONENTS  10.7 INTERNAL ELECTRIC AND COMPONENTS  10.8 CONNECTIONS  10.8 CONNECTIONS FOR EXTERNAL CONDUCTORS  10.9.2 POWER-FREQUENCY ELECTRIC STRENGTH  10.9.3 IMPULSE WITHSTAND VOLTAGE  10.9.4 TESTING OF ENCLOSURES MADE OF INSULATING MATERIAL  Key switch position AUTO Thermo-click Thermistor monitoring PTC Short-circuit release Two sensor inputs through M12 sockets (max. 150 mA) for quick stop and interlocked manual operation Key switch position OFF/RESET  CLASS  CLASS  CLASS  CLASS  CLASS  CLASS  Does not apply, since the entire switchgear needs to be evaluated.  Does not apply, since the entire switchgear needs to be evaluated.  In position apply, since the entire switchgear needs to be evaluated.  Is the panel builder's responsibility.  CLASS  CLASS  CLASS  CLASS  CLASS  CLASS  CLASS  CLASS  CLASS		
IMPACT  IMPACT  IMPACT  INSCRIPTIONS  Meets the product standard's requirements.  Does not apply, since the entire switchgear needs to be evaluated.  Inscription of ASSEMBLIES  Inscription of AUTO Thermo-click Thermistor monitoring PTC  Inscription of AUTO Thermo-click Thermistor moni	10.2.5 LIFTING	entire switchgear needs to
10.2./ TINSCRIPTIONS  10.3 DEGREE OF PROTECTION OF ASSEMBLIES  10.4 CLEARANCES AND CREEPAGE DISTANCES  10.5 PROTECTION AGAINST ELECTRIC SHOCK  10.6 INCORPORATION OF SWITCHING DEVICES AND COMPONENTS  10.7 INTERNAL ELECTRICAL CIRCUITS AND CONNECTIONS  10.8 CONNECTIONS FOR EXTERNAL CONDUCTORS  10.9.2 POWER-FREQUENCY ELECTRIC STRENGTH  10.9.3 IMPULSE WITHSTAND VOLTAGE  10.9.4 TESTING OF ENCLOSURES MADE OF INSULATING MATERIAL  FITTED WITH:  FITTED WITH:  10.2 Does not apply, since the entire switchgear needs to be evaluated.  Does not apply, since the entire switchgear needs to be evaluated.  Is the panel builder's responsibility.  Key switch position HAND Electronic motor protection Key switch position AUTO Thermo-click Thermistor monitoring PTC  Short-circuit release Two sensor inputs through M12 sockets (max. 150 mA) for quick stop and interlocked manual operation Key switch position OFF/RESET		entire switchgear needs to
PROTECTION OF ASSEMBLIES  10.4 CLEARANCES AND CREEPAGE DISTANCES  10.5 PROTECTION AGAINST ELECTRIC SHOCK  10.6 INCORPORATION OF SWITCHING DEVICES AND COMPONENTS  10.7 INTERNAL ELECTRICAL CIRCUITS AND CONNECTIONS  10.8 CONNECTIONS FOR EXTERNAL CONDUCTORS  10.9.2 POWER- FREQUENCY ELECTRIC STRENGTH  10.9.3 IMPULSE WITHSTAND VOLTAGE  10.9.4 TESTING OF ENCLOSURES MADE OF INSULATING MATERIAL  Key switch position HAND Electronic motor protection Key switch position AUTO Thermo-click Thermistor monitoring PTC Short-circuit release Two sensor inputs through M12 sockets (max. 150 mA) for quick stop and interlocked manual operation Key switch position OFF/RESET	10.2.7 INSCRIPTIONS	•
CREEPAGE DISTANCES  10.5 PROTECTION AGAINST ELECTRIC SHOCK  10.6 INCORPORATION OF SWITCHING DEVICES AND COMPONENTS  10.7 INTERNAL ELECTRICAL CIRCUITS AND CONNECTIONS  10.8 CONNECTIONS FOR EXTERNAL CONDUCTORS  10.9.2 POWER- FREQUENCY ELECTRIC STRENGTH  10.9.3 IMPULSE WITHSTAND VOLTAGE  10.9.4 TESTING OF ENCLOSURES MADE OF INSULATING MATERIAL  Key switch position AUTO Thermo-click Thermistor monitoring PTC Short-circuit release Two sensor inputs through M12 sockets (max. 150 mA) for quick stop and interlocked manual operation Key switch position OFF/RESET	PROTECTION OF	entire switchgear needs to
AGAINST ELECTRIC SHOCK  10.6 INCORPORATION OF SWITCHING DEVICES AND COMPONENTS  10.7 INTERNAL ELECTRICAL CIRCUITS AND CONNECTIONS  10.8 CONNECTIONS  10.9.2 POWER- FREQUENCY ELECTRIC STRENGTH  10.9.3 IMPULSE WITHSTAND VOLTAGE  10.9.4 TESTING OF ENCLOSURES MADE OF INSULATING MATERIAL  Key switch position HAND Electronic motor protection Key switch position AUTO Thermo-click Thermistor monitoring PTC Short-circuit release Two sensor inputs through M12 sockets (max. 150 mA) for quick stop and interlocked manual operation Key switch position Key switch position MA) for quick stop and interlocked manual operation Key switch position OFF/RESET		
SWITCHING DEVICES AND COMPONENTS  10.7 INTERNAL ELECTRICAL CIRCUITS AND CONNECTIONS  10.8 CONNECTIONS FOR EXTERNAL CONDUCTORS  10.9.2 POWER-FREQUENCY ELECTRIC STRENGTH  10.9.3 IMPULSE Is the panel builder's responsibility.  10.9.4 TESTING OF ENCLOSURES MADE OF INSULATING MATERIAL  Key switch position HAND Electronic motor protection Key switch position AUTO Thermistor monitoring PTC  FITTED WITH:  SWITCHING DEVICES AND Evaluated.  Esthe panel builder's responsibility.  Is the panel builder's responsibility.  Key switch position HAND Electronic motor protection Key switch position AUTO Thermistor monitoring PTC  Short-circuit release Two sensor inputs through M12 sockets (max. 150 mA) for quick stop and interlocked manual operation Key switch position OFF/RESET	AGAINST ELECTRIC	entire switchgear needs to
Is the panel builder's responsibility.	SWITCHING DEVICES AND	entire switchgear needs to
10.9.2 POWER-FREQUENCY ELECTRIC STRENGTH  10.9.3 IMPULSE Is the panel builder's responsibility.  10.9.4 TESTING OF ENCLOSURES MADE OF INSULATING MATERIAL  Key switch position HAND Electronic motor protection Key switch position AUTO Thermo-click Thermistor monitoring PTC  FITTED WITH:  Short-circuit release Two sensor inputs through M12 sockets (max. 150 mA) for quick stop and interlocked manual operation Key switch position OFF/RESET	ELECTRICAL CIRCUITS	-
Is the panel builder's responsibility.  10.9.3 IMPULSE Is the panel builder's responsibility.  10.9.4 TESTING OF ENCLOSURES MADE OF INSULATING MATERIAL  Key switch position HAND Electronic motor protection Key switch position AUTO Thermo-click Thermistor monitoring PTC  FITTED WITH:  Short-circuit release Two sensor inputs through M12 sockets (max. 150 mA) for quick stop and interlocked manual operation Key switch position OFF/RESET		· · · · · · · · · · · · · · · · · · ·
WITHSTAND VOLTAGE  10.9.4 TESTING OF ENCLOSURES MADE OF INSULATING MATERIAL  Key switch position HAND Electronic motor protection Key switch position AUTO Thermo-click Thermistor monitoring PTC  Short-circuit release Two sensor inputs through M12 sockets (max. 150 mA) for quick stop and interlocked manual operation Key switch position OFF/RESET	FREQUENCY ELECTRIC	•
Is the panel builder's responsibility.  Key switch position HAND Electronic motor protection Key switch position AUTO Thermo-click Thermistor monitoring PTC  FITTED WITH:  Short-circuit release Two sensor inputs through M12 sockets (max. 150 mA) for quick stop and interlocked manual operation Key switch position OFF/RESET		· · · · · · · · · · · · · · · · · · ·
Electronic motor protection Key switch position AUTO Thermo-click Thermistor monitoring PTC Short-circuit release Two sensor inputs through M12 sockets (max. 150 mA) for quick stop and interlocked manual operation Key switch position OFF/RESET	ENCLOSURES MADE OF	-
CLASS 10 A	FITTED WITH:	Electronic motor protection Key switch position AUTO Thermo-click Thermistor monitoring PTC Short-circuit release Two sensor inputs through M12 sockets (max. 150 mA) for quick stop and interlocked manual operation Key switch position OFF/RESET
	CLASS	CLASS 10 A
LIFESPAN, ELECTRICAL 10,000,000 Operations (at AC-3)	LIFESPAN, ELECTRICAL	•

CLIMATIC PROOFING	In accordance with IEC/EN 50178 < 95 %, no condensation
RATED IMPULSE WITHSTAND VOLTAGE (UIMP)	4000 V
MODEL	Direct starter
ALTITUDE	Max. 2000 m Above 1000 m with 1 % performance reduction per 100 m Max. 1000 m
LIFESPAN, MECHANICAL	10,000,000 Operations (at AC-3)
MAINS SWITCH-ON FREQUENCY	Maximum of one time every 60 seconds
ELECTRICAL CONNECTION TYPE OF MAIN CIRCUIT	Plug-in connection
MAINS VOLTAGE TOLERANCE	380 - 480 V (-15 %/+10 %, at 50/60 Hz)
VOLTAGE TYPE	DC
MOUNTING POSITION	Vertical
RATED CONDITIONAL SHORT-CIRCUIT CURRENT (IQ)	10 kA
OVERVOLTAGE CATEGORY	III
CONNECTION	Connections pluggable in power section
OFF-DELAY	20 - 35 ms
FUNCTIONS	Temperature compensated overload protection External reset possible For actuation of motors with mechanical brake
ON-DELAY	20 - 35 ms
SYSTEM CONFIGURATION TYPE	Center-point earthed star network (TN-S network) AC voltage Phase-earthed AC supply systems are not permitted.
BRAKING CURRENT	≤ 0.6 A (max. 6 A for 120 ms), Actuator for external motor brake
ELECTROMAGNETIC COMPATIBILITY	Class A
· · · · · · · · · · · · · · · · · · ·	

CURRENT LIMITATION	0.3 - 6.6 A, motor, main circuit Adjustable, motor, main circuit
OUTPUT FREQUENCY	50/60 Hz
BRAKING VOLTAGE	230/277 V AC -15 % / +10 %, Actuator for external motor brake
OVERLOAD CYCLE	AC-53a
OVERLOAD RELEASE CURRENT SETTING - MIN	0.3 A
RATED CONDITIONAL SHORT-CIRCUIT CURRENT (IQ), TYPE 2, 230 V	0 A
RATED CONDITIONAL SHORT-CIRCUIT CURRENT (IQ), TYPE 2, 380 V, 400 V, 415 V	0 A
RATED CONDITIONAL SHORT-CIRCUIT CURRENT, TYPE 1, 480 Y/277 V	65000 A
RATED CONDITIONAL SHORT-CIRCUIT CURRENT, TYPE 1, 600 Y/347 V	0 A
RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 50 HZ - MAX	0 V
RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 50 HZ - MIN	0 V
RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 60 HZ - MAX	0 V
RATED CONTROL SUPPLY VOLTAGE (US) AT AC, 60 HZ - MIN	0 V
RATED CONTROL SUPPLY VOLTAGE (US) AT DC - MAX	0 V
RATED CONTROL SUPPLY VOLTAGE (US) AT DC - MIN	0 V
RATED FREQUENCY - MAX	63 Hz
RATED FREQUENCY - MIN	47 Hz
RATED OPERATIONAL CURRENT (IE) AT 150% OVERLOAD	6.6 A

RATED OPERATIONAL CURRENT (IE) AT AC-3, 380 V, 400 V, 415 V	6.6 A
SHOCK RESISTANCE	15 g, Mechanical, According to IEC/EN 60068-2-27, 11 ms, Half- sinusoidal shock 11 ms, 1000 shocks per shaft
INTERFACES	Specification: S-7.A.E. (AS-Interface®) Max. total power consumption from AS- Interface® power supply unit (30 V): 190 mA Number of slave addresses: 62 (AS- Interface®)
PROTOCOL	ASI AS-Interface profile cable: S-7.4 for 62 modules
RATED CONTROL VOLTAGE (UC)	24 V DC (-15 %/+20 %, external via AS-Interface® plug) 230/277 V AC (external brake 50/60 Hz)
SUPPLY FREQUENCY	50/60 Hz, fLN, Main circuit
RATED OPERATIONAL CURRENT (IE)	6.6 A
RATED OPERATIONAL POWER AT 380/400 V, 50 HZ - MAX	3 kW
RATED OPERATIONAL POWER AT 380/400 V, 50 HZ - MIN	0.09 kW
RATED OPERATIONAL VOLTAGE	480 V AC, 3-phase 400 V AC, 3-phase
SHORT-CIRCUIT PROTECTION (EXTERNAL OUTPUT CIRCUITS)	Type 1 coordination via the power bus' feeder unit, Main circuit
VIBRATION	Resistance: 57 Hz, Amplitude transition frequency on acceleration Resistance: 6 Hz, Amplitude 0.15 mm Resistance: According to IEC/EN 60068-2-6 Resistance: 10 - 150 Hz, Oscillation frequency
AMBIENT OPERATING TEMPERATURE - MAX	55 °C
	55 °C -10 °C

TEMPERATURE - MIN	
AMBIENT STORAGE TEMPERATURE - MAX	70 °C
AMBIENT STORAGE TEMPERATURE - MIN	-40 °C
ASSIGNED MOTOR POWER AT 460/480 V, 60 HZ, 3-PHASE	3 HP
NUMBER OF AUXILIARY CONTACTS (NORMALLY CLOSED CONTACTS)	0
NUMBER OF AUXILIARY CONTACTS (NORMALLY OPEN CONTACTS)	0
NUMBER OF COMMAND POSITIONS	1
NUMBER OF PILOT LIGHTS	0
OVERLOAD RELEASE CURRENT SETTING - MAX	6.6 A
RATED OPERATIONAL POWER AT AC-3, 220/230 V, 50 HZ	0 kW
RATED OPERATIONAL POWER AT AC-3, 380/400 V, 50 HZ	3 kW
RATED POWER AT 460 V, 60 HZ, 3-PHASE	2.238 kW
RATED POWER AT 575 V, 60 HZ, 3-PHASE	0 kW
PRODUCT CATEGORY	Motor starter
CABLE LENGTH	10 m, Radio interference level, maximum motor cable length
COORDINATION CLASS (IEC 60947-4-3)	Class 1
DEGREE OF PROTECTION	NEMA 12 IP65
ELECTRICAL CONNECTION TYPE FOR AUXILIARY- AND CONTROL-CURRENT CIRCUIT	Plug-in connection
INPUT CURRENT	6.6 A (at 150 % Overload)
POWER CONSUMPTION	8 W

PROJECT NAME:	
PROJECT NUMBER:	
PREPARED BY:	
:	



Eaton House 30 Pembroke Road Dublin 4, Eaton.com

Follow us on social media to get the latest product and support information.









