

00000

Eaton 113243

Eaton Moeller series NZM - Molded Case Circuit Breaker. Circuit-breaker, 3p, 125A, plug-in module, N2-A125-SVE

| 0000 | |
|-------------------------|--|
| PRODUCT NAME | Eaton Moeller series NZM molded case circuit breaker thermo-magnetic |
| CATALOG NUMBER | 113243 |
| PRODUCT LENGTH/DEPTH | 180 mm |
| PRODUCT HEIGHT | 245 mm |
| PRODUCT WIDTH | 105 mm |
| PRODUCT WEIGHT | 2.77 kg |
| COMPLIANCES | RoHS conform |
| CERTIFICATIONS | IEC |



| 0000 | |
|--|--|
| AMPERAGE RATING | 125 A |
| VOLTAGE RATING | 690 V - 690 V |
| FEATURES | Protection unit Motor drive optional |
| 10.10 TEMPERATURE RISE | The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices. |
| 10.11 SHORT-CIRCUIT RATING | Is the panel builder's responsibility. The specifications for the switchgear must be observed. |
| 10.12 ELECTROMAGNETIC COMPATIBILITY | Is the panel builder's responsibility. The specifications for the switchgear must be observed. |
| 10.13 MECHANICAL FUNCTION | The device meets the requirements, provided the information in the instruction leaflet (IL) is observed. |
| 10.2.2 CORROSION RESISTANCE | Meets the product standard's requirements. |
| 10.2.3.1 VERIFICATION OF THERMAL STABILITY OF ENCLOSURES | Meets the product standard's requirements. |
| 10.2.3.2 VERIFICATION OF RESISTANCE OF INSULATING MATERIALS TO NORMAL HEAT | Meets the product standard's requirements. |
| 10.2.3.3 RESIST. OF INSUL. MAT. TO ABNORMAL HEAT/FIRE BY INTERNAL ELECT. EFFECTS | Meets the product standard's requirements. |
| 10.2.4 RESISTANCE TO ULTRA-VIOLET (UV) RADIATION | Meets the product standard's requirements. |
| 10.2.5 LIFTING | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.2.6 MECHANICAL IMPACT | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.2.7 INSCRIPTIONS | Meets the product standard's requirements. |
| 10.3 DEGREE OF PROTECTION OF | Does not apply, since the entire switchgear needs to |

| 00 | |
|----------------------|---|
| CHARACTERISTIC CURVE | eaton-circuit-breaker-let- through-current-nzm- mccb-characteristic-curve- 004.eps |
| | eaton-circuit-breaker-nzm- mccb-characteristic-curve- 050.eps |
| | eaton-circuit-breaker- |
| | <u>characteristic-power-</u> defense-mccb- |
| | characteristic-curve- |
| | <u>036.eps</u> |
| 00000 | eaton-circuit-breaker-plug- in-adapter-nzm2- il01219023z.pdf |

| ACCEMPLIEC | ho ovaluated |
|---|--|
| ASSEMBLIES | be evaluated. |
| 10.4 CLEARANCES AND CREEPAGE DISTANCES | Meets the product standard's requirements. |
| 10.5 PROTECTION AGAINST ELECTRIC SHOCK | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.6 INCORPORATION OF SWITCHING DEVICES AND COMPONENTS | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.7 INTERNAL ELECTRICAL CIRCUITS AND CONNECTIONS | ls the panel builder's responsibility. |
| 10.8 CONNECTIONS FOR EXTERNAL CONDUCTORS | ls the panel builder's responsibility. |
| 10.9.2 POWER- FREQUENCY ELECTRIC STRENGTH | ls the panel builder's responsibility. |
| 10.9.3 IMPULSE WITHSTAND VOLTAGE | ls the panel builder's responsibility. |
| 10.9.4 TESTING OF ENCLOSURES MADE OF INSULATING MATERIAL | ls the panel builder's responsibility. |
| MOUNTING METHOD | Built-in device plug-in technique Plug-in unit DIN rail (top hat rail) mounting optional |
| EQUIPMENT HEAT DISSIPATION, CURRENT- DEPENDENT | 27.61 W |
| AMBIENT OPERATING TEMPERATURE - MAX | 70 °C |
| AMBIENT OPERATING TEMPERATURE - MIN | -25 °C |
| AMBIENT STORAGE TEMPERATURE - MAX | 70 °C |
| AMBIENT STORAGE TEMPERATURE - MIN | 40 °C |
| NUMBER OF AUXILIARY CONTACTS (CHANGE- OVER CONTACTS) | 0 |
| NUMBER OF AUXILIARY CONTACTS (NORMALLY CLOSED CONTACTS) | 0 |
| NUMBER OF AUXILIARY CONTACTS (NORMALLY OPEN CONTACTS) | 0 |
| DEGREE OF PROTECTION | IP20 |
| ELECTRICAL CONNECTION TYPE OF MAIN CIRCUIT | Screw connection |

| NUMBER OF POLES | Three-pole |
|--|--|
| SPECIAL FEATURES | Rated current = rated uninterrupted current: 125 A |
| POSITION OF CONNECTION FOR MAIN CURRENT CIRCUIT | Front side |
| POWER LOSS | 27.6 W |
| SHORT-CIRCUIT RELEASE NON-DELAYED SETTING - MAX | 1250 A |
| SHORT-CIRCUIT RELEASE NON-DELAYED SETTING - MIN | 750 A |
| HANDLE TYPE | Rocker lever |
| SHORT DELAY CURRENT SETTING (ISD) - MAX | 0 A |
| SHORT DELAY CURRENT SETTING (ISD) - MIN | 0 A |
| INSTANTANEOUS CURRENT SETTING (II) - MAX | 1250 A |
| INSTANTANEOUS CURRENT SETTING (II) - MIN | 750 A |
| OVERLOAD CURRENT SETTING (IR) - MAX | 125 A |
| OVERLOAD CURRENT SETTING (IR) - MIN | 100 A |
| RATED SHORT-CIRCUIT BREAKING CAPACITY ICS (IEC/EN 60947) AT 400/415 V, 50/60 HZ | 50 kA |
| RATED SHORT-CIRCUIT BREAKING CAPACITY ICS (IEC/EN 60947) AT 500 V DC | 7.5 kA |
| RATED SHORT-CIRCUIT BREAKING CAPACITY ICS (IEC/EN 60947) AT 750 V DC | 7.5 kA |
| STANDARD TERMINALS | Screw terminal |

| PROJECT NAME: | |
|-----------------|--|
| PROJECT NUMBER: | |
| PREPARED BY: | |
| ПП: | |



Eaton House 30 Pembroke Road Dublin 4, □□□ Eaton.com

Follow us on social media to get the latest product and support information.









