Eaton 177366

Eaton DE1 Variable speed starter, Rated operational voltage 400 V AC, 3-phase, le 2.1 A, 0.75 kW, 1 HP

| PRODUCT NAME | Eaton DE1 Variable speed starter |
|-------------------------|---|
| CATALOG NUMBER | 177366 |
| PRODUCT LENGTH/DEPTH | 169 mm |
| PRODUCT HEIGHT | 230 mm |
| PRODUCT WIDTH | 45 mm |
| PRODUCT WEIGHT | 1 kg |
| CERTIFICATIONS | Certified by UL for use in Canada UL File No.: E172143 Specification for general requirements: IEC/EN 61800-2 RoHS, ISO 9001 UL Category Control No.: NMMS, NMMS7 UL RCM Safety requirements: IEC/EN 61800-5-1 CSA-C22.2 No. 14 CUL UL 508C IEC/EN61800-3 CE UL report applies to both US and Canada IEC/EN 61800-5 |
| CATALOG NOTES | Overload cycle for 60 s every 600 s |



| Parameterization: drivesConnect Parameterization: drivesConnect mobile (App) Parameterization: Fieldbus Parameterization: Keypad The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices. Is the panel builder's |
|---|
| The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices. Is the panel builder's |
| • |
| 10.11 SHORT-CIRCUIT RATING responsibility. The specifications for the switchgear must be observed. |
| 10.12 ELECTROMAGNETIC COMPATIBILITY Is the panel builder's responsibility. The specifications for the switchgear must be observed. |
| 10.13 MECHANICAL FUNCTION The device meets the requirements, provided the information in the instruction leaflet (IL) is observed. |
| 10.2.2 CORROSIONMeets the productRESISTANCEstandard's requirements. |
| 10.2.3.1 VERIFICATION OF THERMAL STABILITY OF ENCLOSURES Meets the product standard's requirements. |
| 10.2.3.2 VERIFICATION OF RESISTANCE OF Meets the product INSULATING MATERIALS TO NORMAL HEAT Meets the product standard's requirements. |
| 10.2.3.3 RESIST. OF INSUL. MAT. TO ABNORMAL HEAT/FIRE BY INTERNAL ELECT. EFFECTS Meets the product standard's requirements. |
| 10.2.4 RESISTANCE TO ULTRA-VIOLET (UV) RADIATION Meets the product standard's requirements. |
| |
| Does not apply, since the entire switchgear needs to be evaluated. |

| DECLARATIONS OF | DA-DC-00004551.pdf |
|-----------------|--|
| CONFORMITY | DA-DC-00004556.pdf |
| | <u>IL040005ZU</u> |
| | eaton-powerxl-de1- variable-speed-starter- brochure-br040003en-en- us.pdf |
| | eaton-powerxl-variable- frequency-drives-hvac- brochure-br040012en-en- us.pdf |
| | eaton-de1-variable-speed- starter-manual- mn040011-zh-cn.pdf |
| | eaton-de1-variable-speed- starter-manual- mn040011-hu-hu.pdf |
| | eaton-frequency-inverter- dimensions-009.eps |
| | eaton-frequency-inverter- 3d-drawing-017.eps |
| | How does the internal motor protection work? |
| | DX-COM- STICK3 Connection |
| | The OP System Bus - Parameterizing - Control |

| IMPACT | entire switchgear needs to be evaluated. |
|--|---|
| 10.2.7 INSCRIPTIONS | Meets the product standard's requirements. |
| 10.3 DEGREE OF PROTECTION OF ASSEMBLIES | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.4 CLEARANCES AND CREEPAGE DISTANCES | Meets the product standard's requirements. |
| 10.5 PROTECTION AGAINST ELECTRIC SHOCK | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.6 INCORPORATION OF SWITCHING DEVICES AND COMPONENTS | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.7 INTERNAL ELECTRICAL CIRCUITS AND CONNECTIONS | ls the panel builder's responsibility. |
| 10.8 CONNECTIONS FOR EXTERNAL CONDUCTORS | ls the panel builder's responsibility. |
| 10.9.2 POWER- FREQUENCY ELECTRIC STRENGTH | ls the panel builder's responsibility. |
| 10.9.3 IMPULSE WITHSTAND VOLTAGE | ls the panel builder's responsibility. |
| 10.9.4 TESTING OF ENCLOSURES MADE OF INSULATING MATERIAL | Is the panel builder's responsibility. |
| FITTED WITH: | PC connection |
| CLIMATIC PROOFING | < 95 average relative humidity (RH), no condensation, no corrosion |
| CONNECTION TO SMARTWIRE-DT | Yes In conjunction with DX- NET-SWD3 SmartWire DT module |
| OPERATING MODE | Speed control with slip compensation U/f control |
| RATED IMPULSE WITHSTAND VOLTAGE (UIMP) | 2000 V |
| FRAME SIZE | FS1 |
| ALTITUDE | Above 1000 m with 1 % derating per 100 m Max. 2000 m |
| APPLICATION IN DOMESTIC AND | Yes |

| COMMERCIAL AREA PERMITTED | |
|--|--|
| MAINS SWITCH-ON FREQUENCY | Maximum of one time every 30 seconds |
| AMBIENT OPERATING TEMPERATURE - MAX | 60 °C |
| AMBIENT OPERATING TEMPERATURE - MIN | -10 °C |
| MAINS VOLTAGE - MAX | 480 V |
| OUTPUT VOLTAGE - MAX | 500 V |
| RELATIVE SYMMETRIC NET FREQUENCY TOLERANCE | 10 % |
| RELATIVE SYMMETRIC NET VOLTAGE TOLERANCE | 10 % |
| AMBIENT OPERATING TEMPERATURE AT 150% OVERLOAD - MAX | 50 °C |
| AMBIENT OPERATING TEMPERATURE AT 150% OVERLOAD - MIN | -10 °C |
| AMBIENT STORAGE TEMPERATURE - MAX | 70 °C |
| AMBIENT STORAGE TEMPERATURE - MIN | -40 °C |
| APPARENT POWER AT 400 V | 1.45 kVA |
| APPARENT POWER AT 480 V | 1.75 kVA |
| APPLICATION IN INDUSTRIAL AREA PERMITTED | Yes |
| AMBIENT OPERATING TEMPERATURE DETAILS | Derating between 50 °C and 60 °C: None if fPWM ≤ 16 kHz None if fPWM ≤ 20 kHz up to a max. of 57 °C None if I_e ≤ 1.6 A |
| HEAT DISSIPATION DETAILS | Operation (with 150 % overload) |
| PRODUCT CATEGORY | Variable speed starter |
| PROTECTION | Finger and back-of-hand proof, Protection against direct contact (BGV A3, VBG4) |

| RESOLUTION | 0.025 Hz (Frequency resolution, setpoint value) |
|---|--|
| STATIC HEAT DISSIPATION, NON- CURRENT-DEPENDENT PVS | 0 W |
| VOLTAGE RATING - MAX | 480 V |
| MOUNTING POSITION | Vertical |
| OVERVOLTAGE CATEGORY | III |
| COMMUNICATION INTERFACE | OP-Bus (RS485), built in Modbus RTU, built in |
| CONVERTER TYPE | U converter |
| DEGREE OF PROTECTION | IP20 NEMA Other |
| ASSIGNED MOTOR POWER AT 460/480 V, 60 HZ, 3-PHASE | 1 HP |
| EQUIPMENT HEAT DISSIPATION, CURRENT- DEPENDENT PVID | 28 W |
| HEAT DISSIPATION CAPACITY PDISS | 0 W |
| HEAT DISSIPATION PER POLE, CURRENT- DEPENDENT PVID | 0 W |
| INPUT CURRENT ILN AT 150% OVERLOAD | 3.1 A |
| MAINS CURRENT DISTORTION | 120 % |
| PROTOCOL | MODBUS EtherNet/IP Other bus systems |
| OVERLOAD CURRENT IL AT 150% OVERLOAD | 3.15 A |
| RATED FREQUENCY - MAX | 66 Hz |
| RATED FREQUENCY - MIN | 45 Hz |
| RATED OPERATIONAL CURRENT FOR SPECIFIED HEAT DISSIPATION (IN) | 2.1 A |
| RATED OPERATIONAL POWER AT 380/400 V, 50 HZ, 3-PHASE | 0.75 kW |
| ASSIGNED MOTOR CURRENT IM AT 400 V, 50 HZ, 150% OVERLOAD | 1.9 A |
| ASSIGNED MOTOR | 2.1 A |
| | |

| BRAKING CURRENT ≤ 0.6 A (max. 6 A for 120 ms), Actuator for external motor brakeELECTROMAGNETIC COMPATIBILITY1st and 2nd environments (according to EN 61800-3)BRAKING TORQUEAdjustable to 100 %, DC - Main circuit Max. 30 % MN, Standard - Main circuitC3 ≤ 25 m, Radio interference level, maximum motor cable length $C2 \leq 10$ m, Radio interference level, maximum motor cable length |
|---|
| COMPATIBILITY(according to EN 61800-3)BRAKING TORQUEAdjustable to 100 %, DC - Main circuit Max. 30 % MN, Standard - Main circuitC3 \leq 25 m, Radio interference level, maximum motor cable length C2 \leq 10 m, Radio interference level, maximum motor cable |
| BRAKING TORQUE |
| interference level, maximum motor cable length C2 ≤ 10 m, Radio interference level, maximum motor cable |
| |
| OUTPUT VOLTAGE (U2) 400 V AC, 3-phase 480 V AC, 3-phase |
| VELAY TIME < 10 ms, On-delay < 10 ms, Off-delay |
| NUMBER OF INPUTS 1 (parameterizable, 0 - 10 (ANALOG) V DC, 0/4 - 20 mA) |
| NUMBER OF INPUTS 4 (parameterizable, 10 - 30 (DIGITAL) V DC) |
| C2, C3: depending on the motor cable length, the connected load, and ambient conditions. External radio interference suppression filters (optional) may be CLASS necessary. Optional external radio interference suppression filter for longer motor cable lengths and for use in different EMC environments |
| NUMBER OF OUTPUTS (DIGITAL) |
| STARTING CURRENT - 200 %, IH, max. starting current (High Overload), For 1.875 seconds every 600 seconds, Power section |
| NUMBER OF PHASES (INPUT) |

| NUMBER OF RELAY OUTPUTS | 1 (parameterizable, N/O, 6 A (250 V, AC-1) / 5 A (30 V, DC-1)) |
|--|--|
| NUMBER OF PHASES (OUTPUT) | 3 |
| POWER CONSUMPTION | 28 W |
| RATED CONTROL SUPPLY VOLTAGE | 10 V DC (Us, max. 0.2 mA) |
| SUPPLY FREQUENCY | 50/60 Hz |
| LEAKAGE CURRENT AT GROUND IPE - MAX | < 10 mA (DC-operated) < 3.5 mA (AC-operated) |
| MAINS VOLTAGE - MIN | 380 V |
| NOMINAL OUTPUT CURRENT I2N | 2.1 A |
| NUMBER OF HW- INTERFACES (INDUSTRIAL ETHERNET) | 0 |
| NUMBER OF HW- INTERFACES (OTHER) | 0 |
| NUMBER OF HW- INTERFACES (PARALLEL) | 0 |
| NUMBER OF HW- INTERFACES (RS-232) | 0 |
| NUMBER OF HW- INTERFACES (RS-422) | 0 |
| NUMBER OF HW- INTERFACES (RS-485) | 1 |
| NUMBER OF HW- INTERFACES (SERIAL TTY) | 0 |
| NUMBER OF HW- INTERFACES (USB) | 0 |
| NUMBER OF INTERFACES (PROFINET) | 0 |
| NUMBER OF OUTPUTS (ANALOG) | 0 |
| OUTPUT AT LINEAR LOAD AT RATED OUTPUT VOLTAGE - MAX | 0.75 kW |
| OUTPUT AT QUADRATIC LOAD AT RATED OUTPUT VOLTAGE - MAX | 0.75 kW |
| OUTPUT FREQUENCY - MAX | 300 Hz |
| OUTPUT FREQUENCY - MIN | 0 Hz |
| SHORT-CIRCUIT PROTECTION (EXTERNAL OUTPUT CIRCUITS) | Type 1 coordination via the power bus' feeder unit, Main circuit |

| SHOCK RESISTANCE | 15 g, Mechanical, According to IEC/EN 60068-2-27, 11 ms |
|-----------------------------------|---|
| SUITABLE FOR | Branch circuits, (UL/CSA) |
| SWITCHING FREQUENCY | 16 kHz, 4 - 32 kHz adjustable (audible), fPWM, Power section, Main circuit |
| RATED OPERATIONAL CURRENT (IE) | 2.1 A at 150% overload (at an operating frequency of 16 kHz and an ambient air temperature of +50 °C) |
| RATED OPERATIONAL VOLTAGE | 480 V AC, 3-phase 400 V AC, 3-phase |
| SHORT-CIRCUIT PROTECTION RATING | 6 A, UL (Class CC or J), Safety device (fuse or miniature circuit-breaker), Power Wiring |
| VIBRATION | Resistance: According to EN 61800-5-1 |
| HEAT DISSIPATION AT CURRENT/SPEED | 11.8 W at 50% current and 0% speed 14.3 W at 25% current and 0% speed 14.3 W at 25% current and 50% speed 16.7 W at 50% current and 90% speed 17.2 W at 50% current and 50% speed 25.4 W at 100% current and 0% speed 26.8 W at 100% current and 90% speed 27.9 W at 100% current and 50% speed |

| PROJECT NAME: | |
|-----------------|--|
| PROJECT NUMBER: | |
| PREPARED BY: | |
| : | |



Follow us on social media to get the Eaton House latest product and support information.

Dublin 4,











Eaton.com