Eaton 198558

Eaton Moeller® series Rapid Link - Speed controller, 4.3 A, 1.5 kW, Sensor input 4, 230/277 V AC, AS-Interface®, S-7.4 for 31 modules, HAN Q5, with braking resistance

PRODUCT NAME	Eaton Rapid Link Speed controller	
CATALOG NUMBER	198558	
PRODUCT LENGTH/DEPTH	157 mm	
PRODUCT HEIGHT	270 mm	
PRODUCT WIDTH	220 mm	
PRODUCT WEIGHT	3.42 kg	
CERTIFICATIONS	CE UL approval IEC/EN 61800-5-1 RoHS UL 61800-5-1	
CATALOG NOTES	 can be switched over from U/f to (vector) speed control Connection of supply voltage via adapter cable on round or flexible busbar junction Diagnostics and reset on device and via AS-Interface Four fixed speeds integrated PTC thermistor monitoring and Thermoclick with safe isolation optional: 4 sensor inputs with M12-Y adapter for switchover to creep speed 	



- optional: Faster stop if external 24 V fails
- Two sensor inputs through M12 sockets (max. 150 mA) for quick stop and interlocked manual operation
- with AUTO -OFF/RESET - HAND key switches
- with selector switch REV - OFF - FWD

FEATURES	Parameterization: drivesConnect mobile (App) Parameterization: drivesConnect Diagnostics and reset on device and via AS-Interface Parameterization: Keypad	
10.10 TEMPERATURE RISE	Parameterization: Fieldbus The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.	
10.11 SHORT-CIRCUIT RATING	Is the panel builder's responsibility. The specifications for the switchgear must be observed.	
10.12 ELECTROMAGNETIC COMPATIBILITY	Is the panel builder's responsibility. The specifications for the switchgear must be observed.	
10.13 MECHANICAL FUNCTION	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.	
10.2.2 CORROSION RESISTANCE	Meets the product standard's requirements.	
10.2.3.1 VERIFICATION OF THERMAL STABILITY OF ENCLOSURES	Meets the product standard's requirements.	
10.2.3.2 VERIFICATION OF RESISTANCE OF INSULATING MATERIALS TO NORMAL HEAT	Meets the product standard's requirements.	
10.2.3.3 RESIST. OF INSUL. MAT. TO ABNORMAL HEAT/FIRE BY INTERNAL ELECT. EFFECTS	Meets the product standard's requirements.	
10.2.4 RESISTANCE TO ULTRA-VIOLET (UV) RADIATION	Meets the product standard's requirements.	
10.2.5 LIFTING	Does not apply, since the entire switchgear needs to be evaluated.	

	ETN.RASP5-4402A31-	
ECAD MODEL	5120100S1.edz	
MCAD MODEL	rasp5 v19.stp	
	ramo5_v19.dwg	
	eaton-powerxl-speed- control-unit-as-interface- rasp5-il034085zu.pdf	
	eaton-rapid-link-5- brochure-br040014en-en- us.pdf	
	eaton-rapid-link-5- mn034004en-us.pdf	
	eaton-bus-adapter- rapidlink-speed-controller- dimensions.eps	
	eaton-bus-adapter- rapidlink-speed-controller- dimensions-003.eps	
	eaton-bus-adapter- rapidlink-speed-controller- dimensions-002.eps	
	eaton-bus-adapter- rapidlink-speed-controller- dimensions-004.eps	

10.2.6 MECHANICAL IMPACT	Does not apply, since the entire switchgear needs to be evaluated.	
10.2.7 INSCRIPTIONS	Meets the product standard's requirements.	
10.3 DEGREE OF PROTECTION OF ASSEMBLIES	Does not apply, since the entire switchgear needs to be evaluated.	
10.4 CLEARANCES AND CREEPAGE DISTANCES	Meets the product standard's requirements.	
10.5 PROTECTION AGAINST ELECTRIC SHOCK	Does not apply, since the entire switchgear needs to be evaluated.	
10.6 INCORPORATION OF SWITCHING DEVICES AND COMPONENTS	Does not apply, since the entire switchgear needs to be evaluated.	
10.7 INTERNAL ELECTRICAL CIRCUITS AND CONNECTIONS	ls the panel builder's responsibility.	
10.8 CONNECTIONS FOR EXTERNAL CONDUCTORS	ls the panel builder's responsibility.	
10.9.2 POWER- FREQUENCY ELECTRIC STRENGTH	ls the panel builder's responsibility.	
10.9.3 IMPULSE WITHSTAND VOLTAGE	ls the panel builder's responsibility.	
10.9.4 TESTING OF ENCLOSURES MADE OF INSULATING MATERIAL	ls the panel builder's responsibility.	
FITTED WITH:	Key switch position HAND Selector switch (Positions: REV - OFF - FWD) Key switch position AUTO Key switch position OFF/RESET Four fixed speeds Control unit Breaking resistance Thermo-click with safe isolation IGBT inverter Two sensor inputs through M12 sockets (max. 150 mA) for quick stop and interlocked manual operation PTC thermistor monitoring Internal DC link PC connection Braking resistance	
CLIMATIC PROOFING	In accordance with IEC/EN	

	50178 < 95 %, no condensation	
OPERATING MODE	Synchronous reluctance motors Sensorless vector control (SLV) U/f control BLDC motors PM and LSPM motors	
RATED IMPULSE WITHSTAND VOLTAGE (UIMP)	2000 V	
ALTITUDE	Above 1000 m with 1 % performance reduction per 100 m Max. 2000 m	
APPLICATION IN DOMESTIC AND COMMERCIAL AREA PERMITTED	Yes	
MAINS SWITCH-ON FREQUENCY	Maximum of one time every 60 seconds	
AMBIENT OPERATING TEMPERATURE - MAX	40 °C	
AMBIENT OPERATING TEMPERATURE - MIN	-10 °C	
MAINS VOLTAGE - MAX	480 V	
OUTPUT VOLTAGE - MAX	500 V	
RELATIVE SYMMETRIC NET FREQUENCY TOLERANCE	10 %	
RELATIVE SYMMETRIC NET VOLTAGE TOLERANCE	10 %	
AMBIENT STORAGE TEMPERATURE - MAX	70 °C	
AMBIENT STORAGE TEMPERATURE - MIN	-40 °C	
APPLICATION IN INDUSTRIAL AREA PERMITTED	Yes	
MAINS VOLTAGE TOLERANCE	380 - 480 V (-10 %/+10 %, at 50/60 Hz)	
PRODUCT CATEGORY	Speed controller	
PROTECTION	Finger and back-of-hand proof, Protection against direct contact (BGV A3, VBG4)	
RESOLUTION	0.1 Hz (Frequency	

	resolution, setpoint value)	
SWITCH-ON THRESHOLD FOR THE BRAKING TRANSISTOR	765 VDC	
MOUNTING POSITION	Vertical	
RATED CONDITIONAL SHORT-CIRCUIT CURRENT (IQ)	10 kA	
OVERVOLTAGE CATEGORY	III	
COMMUNICATION INTERFACE	AS-Interface	
CONNECTION	Plug type: HAN Q5	
CONVERTER TYPE	U converter	
DEGREE OF PROTECTION	NEMA 12 IP65	
ASSIGNED MOTOR POWER AT 460/480 V, 60 HZ, 3-PHASE	2 HP	
HEAT DISSIPATION CAPACITY PDISS	0 W	
HEAT DISSIPATION PER POLE, CURRENT- DEPENDENT PVID	0 W	
INPUT CURRENT ILN AT 150% OVERLOAD	4.1 A	
MAINS CURRENT DISTORTION	120 %	
PROTOCOL	AS-Interface profile cable: S-7.4 for 31 modules ASI	
OVERLOAD CURRENT	At 40 °C For 60 s every 600 s	
OVERLOAD CURRENT IL AT 150% OVERLOAD	6.5 A	
RATED FREQUENCY - MAX	66 Hz	
RATED FREQUENCY - MIN	45 Hz	
RATED OPERATIONAL POWER AT 380/400 V, 50 HZ, 3-PHASE	0.75 kW	
ASSIGNED MOTOR CURRENT IM AT 400 V, 50 HZ, 150% OVERLOAD	4.3 A	
ASSIGNED MOTOR CURRENT IM AT 440 - 480 V, 60 HZ, 150% OVERLOAD	4.3 A	

SYSTEM CONFIGURATION TYPE Phase-earthed AC supply systems are not permitted. ≤ 0.6 A (max. 6 A for 120 ms), Actuator for external motor brake ELECTROMAGNETIC COMPATIBILITY CURRENT LIMITATION BRAKING TORQUE BRAKING VOLTAGE CABLE LENGTH CABLE LENGTH CABLE LENGTH CABLE LENGTH CABLE LENGTH CONFIGURATION CENTER TORQUE CABLE LENGTH CABLE LE
BRAKING CURRENT ms), Actuator for external motor brake ELECTROMAGNETIC (according to EN 61800-3) Adjustable, motor, main circuit 0.4 - 4.3 A, motor, main circuit Adjustable to 100 % (I/Ie), DC - Main circuit ≤ 30 % (I/Ie) BRAKING TORQUE BRAKING VOLTAGE CABLE LENGTH CABLE LENGTH CABLE LENGTH CABLE LENGTH PUNCTIONS ms), Actuator for external motor, main circuit ≤ 30 % (I/Ie) 230/277 V AC -15 % / +10 %, Actuator for external motor brake C3 ≤ 25 m, maximum motor cable length C1 ≤ 1 m, maximum motor cable length C2 ≤ 5 m, maximum motor cable length C1 ≤ 1 m, maximum motor cable length C2 ≤ 5 m, maximum motor cable length C3 ≤ 25 m, maximum motor cable length C1 ≤ 1 m, maximum motor cable length C3 ≤ 25 m, maximum motor cable length C1 ≤ 1 m, maximum motor cable length C2 ≤ 5 m, maximum motor cable length C3 ≤ 5 m, maximum motor cable length C4 ← 10 maximum motor cable length C5 ≤ 5 m, maximum motor cable length C6 ≤ 5 m, maximum motor cable length C7 ≤ 10 m, maximum motor cable length C9 ≤ 10 m, maximum motor cable length C1 ≤ 1 m, maximum motor cable length C7 ≤ 5 m, maximum motor cable length C8 ≤ 10 m, maximum motor cable length C9 ≤ 10 m, maximum motor cable length C1 ≤ 1 m, maximum motor cable length C1 ≤ 1 m, maximum motor cable length C1 ≤ 1 m, maximum motor cable length C2 ≤ 5 m, maximum motor cable length C3 ≤ 10 m, maximum motor cable len
COMPATIBILITY (according to EN 61800-3) Adjustable, motor, main circuit 0.4 - 4.3 A, motor, main circuit BRAKING TORQUE Adjustable to 100 % (I/Ie), DC - Main circuit ≤ 30 % (I/Ie) BRAKING VOLTAGE 230/277 V AC -15 % / +10 %, Actuator for external motor brake CABLE LENGTH C3 ≤ 25 m, maximum motor cable length C1 ≤ 1 m, maximum motor cable length C2 ≤ 5 m, maximum motor cable length FUNCTIONS 4-quadrant operation possible For actuation of motors with mechanical brake Brake chopper with braking resistance for dynamic braking PELAY TIME < 10 ms, Off-delay
CURRENT LIMITATION circuit 0.4 - 4.3 A, motor, main circuit Adjustable to 100 % (I/Ie), DC - Main circuit ≤ 30 % (I/Ie) 230/277 V AC -15 % / +10 %, Actuator for external motor brake C3 ≤ 25 m, maximum motor cable length C1 ≤ 1 m, maximum motor cable length C2 ≤ 5 m, maximum motor cable length C1 ≤ 1 m, maximum motor cable length C2 ≤ 5 m, maximum motor cable length C3 ≤ 25 m, maximum motor cable length C1 ≤ 1 m, maximum motor cable length C3 ≤ 25 m, maximum motor cable length C1 ≤ 1 m, maximum motor cable length C3 ≤ 5 m, maximum motor cable length C3 ≤ 5 m, maximum motor cable length C3 ≤ 25 m, maximum motor cable length C3 ≤ 25 m, maximum motor cable length C3 ≤ 5 m, maximum motor cable length C3 ≤ 5 m, maximum motor cable length C4 quadrant operation possible For actuation of motors with mechanical brake Brake chopper with brake chopper with brake chopper with c 10 ms, Off-delay
BRAKING TORQUE DC - Main circuit ≤ 30 % (I/Ie) 230/277 V AC -15 % / +10 %, Actuator for external motor brake C3 ≤ 25 m, maximum motor cable length C1 ≤ 1 m, maximum motor cable length C2 ≤ 5 m, maximum motor cable length 4-quadrant operation possible For actuation of motors with mechanical brake Brake chopper with braking resistance for dynamic braking < 10 ms, Off-delay
BRAKING VOLTAGE %, Actuator for external motor brake C3 ≤ 25 m, maximum motor cable length C1 ≤ 1 m, maximum motor cable length C2 ≤ 5 m, maximum motor cable length 4-quadrant operation possible For actuation of motors with mechanical brake Brake chopper with braking resistance for dynamic braking < 10 ms, Off-delay
TELAY TIME CABLE LENGTH C1 ≤ 1 m, maximum motor cable length C2 ≤ 5 m, maximum motor cable length 4-quadrant operation possible For actuation of motors with mechanical brake Brake chopper with braking resistance for dynamic braking < 10 ms, Off-delay
possible For actuation of motors with mechanical brake Brake chopper with braking resistance for dynamic braking < 10 ms, Off-delay
I)FI AY IIMF
< 10 ms, On-delay
NUMBER OF INPUTS (ANALOG)
NUMBER OF INPUTS (DIGITAL)
C1: for conducted emissions only C2, C3: depending on the motor cable length, the connected load, and ambient conditions. External radio interference suppression filters (optional) may be necessary.
NUMBER OF OUTPUTS (DIGITAL)

STARTING CURRENT - MAX	200 %, IH, max. starting current (High Overload), For 2 seconds every 20 seconds, Power section	
NUMBER OF PHASES (INPUT)	3	
NUMBER OF PHASES (OUTPUT)	3	
POWER CONSUMPTION	46 W	
INTERFACES	Number of slave addresses: 31 (AS- Interface®) Specification: S-7.4 (AS- Interface®) Max. total power consumption from AS- Interface® power supply unit (30 V): 190 mA	
EFFICIENCY	98 % (η)	
RATED CONTROL VOLTAGE (UC)	24 V DC (-15 %/+20 %, external via AS-Interface® plug) 230/277 V AC (external brake 50/60 Hz)	
SUPPLY FREQUENCY	50/60 Hz	
LEAKAGE CURRENT AT GROUND IPE - MAX	3.5 mA	
MAINS VOLTAGE - MIN	380 V	
NOMINAL OUTPUT CURRENT I2N	4.3 A	
NUMBER OF HW- INTERFACES (INDUSTRIAL ETHERNET)	0	
NUMBER OF HW- INTERFACES (OTHER)	1	
NUMBER OF HW- INTERFACES (PARALLEL)	0	
NUMBER OF HW- INTERFACES (RS-232)	0	
NUMBER OF HW- INTERFACES (RS-422)	0	
NUMBER OF HW- INTERFACES (RS-485)	1	
NUMBER OF HW- INTERFACES (SERIAL TTY)	0	
NUMBER OF HW- INTERFACES (USB)	0	
NUMBER OF INTERFACES (PROFINET)	0	

NUMBER OF OUTPUTS (ANALOG)	0	
OUTPUT AT LINEAR LOAD AT RATED OUTPUT VOLTAGE - MAX	1.5 kW	
OUTPUT AT QUADRATIC LOAD AT RATED OUTPUT VOLTAGE - MAX	1.5 kW	
OUTPUT FREQUENCY - MAX	500 Hz	
OUTPUT FREQUENCY - MIN	0 Hz	
SHORT-CIRCUIT PROTECTION (EXTERNAL OUTPUT CIRCUITS)	Type 1 coordination via the power bus' feeder unit, Main circuit	
SHOCK RESISTANCE	15 g, Mechanical, According to IEC/EN 60068-2-27, 11 ms, Half- sinusoidal shock 11 ms, 1000 shocks per shaft	
SWITCHING FREQUENCY	8 kHz, 4 - 32 kHz adjustable, fPWM, Power section, Main circuit	
RATED OPERATIONAL CURRENT (IE)	4.3 A at 150% overload (at an operating frequency of 8 kHz and an ambient air temperature of +40 °C)	
RATED OPERATIONAL VOLTAGE	480 V AC, 3-phase 400 V AC, 3-phase	
VIBRATION	Resistance: 57 Hz, Amplitude transition frequency on acceleration Resistance: 6 Hz, Amplitude 0.15 mm Resistance: According to IEC/EN 60068-2-6 Resistance: 10 - 150 Hz, Oscillation frequency	
HEAT DISSIPATION AT CURRENT/SPEED	32.3 W at 25% current and 0% speed 33.2 W at 25% current and 50% speed 35.2 W at 50% current and 90% speed 36.2 W at 50% current and 0% speed 37.6 W at 50% current and 50% speed 46.3 W at 100% current and 90% speed 48.7 W at 100% current and 0% speed	

PROJEC	· NA	ME:
--------	------	-----

PROJECT NUMBER:

PREPARED BY:



Eaton House 30 Pembroke Road Dublin 4, Eaton.com

Follow us on social media to get the latest product and support information.









