

Eaton 265782

Eaton Moeller series NZM - Molded Case Circuit Breaker. Circuit-breaker, 3p, 350A, NZMN3-ME350

| 0000 | |
|-------------------------|---|
| PRODUCT NAME | Eaton Moeller series NZM molded case circuit breaker electronic |
| CATALOG NUMBER | 265782 |
| PRODUCT LENGTH/DEPTH | 166 mm |
| PRODUCT HEIGHT | 275 mm |
| PRODUCT WIDTH | 140 mm |
| PRODUCT WEIGHT | 6.914 kg |
| COMPLIANCES | RoHS conform |
| CERTIFICATIONS | IEC/EN 60947 IEC |



| AMPERAGE RATING | 350 A |
|---|--|
| VOLTAGE RATING | 690 V - 690 V |
| CIRCUIT BREAKER FRAME TYPE | NZM3 |
| 10.10 TEMPERATURE RISE | The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices. |
| 10.11 SHORT-CIRCUIT RATING | ls the panel builder's responsibility. The specifications for the switchgear must be observed. |
| 10.12 ELECTROMAGNETIC COMPATIBILITY | Is the panel builder's responsibility. The specifications for the switchgear must be observed. |
| 10.13 MECHANICAL FUNCTION | The device meets the requirements, provided the information in the instruction leaflet (IL) is observed. |
| 10.2.2 CORROSION RESISTANCE | Meets the product standard's requirements. |
| 10.2.3.1 VERIFICATION OF THERMAL STABILITY OF ENCLOSURES | Meets the product standard's requirements. |
| 10.2.3.2 VERIFICATION OF RESISTANCE OF INSULATING MATERIALS TO NORMAL HEAT | Meets the product standard's requirements. |
| 10.2.3.3 RESIST. OF INSUL. MAT. TO ABNORMAL HEAT/FIRE BY INTERNAL ELECT. EFFECTS | Meets the product standard's requirements. |
| 10.2.4 RESISTANCE TO ULTRA-VIOLET (UV) RADIATION | Meets the product standard's requirements. |
| 10.2.5 LIFTING | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.2.6 MECHANICAL IMPACT | Does not apply, since the entire switchgear needs to be evaluated. |
| 10.2.7 INSCRIPTIONS | Meets the product standard's requirements. |
| 10.3 DEGREE OF PROTECTION OF | Does not apply, since the entire switchgear needs to |

| CHARACTERISTIC CURVE | eaton-circuit-breaker-nzm- mccb-characteristic-curve- 017.eps | |
|----------------------|---|--|
| | eaton-circuit-breaker-nzm- mccb-characteristic-curve- 056.eps | |
| | eaton-circuit-breaker-let- through-current-nzm- mccb-characteristic-curve- 006.eps | |
| 00000 | eaton-circuit-breaker- basic-device-nzmn-b- il01208009z.pdf | |
| 000 | eaton-manual-motor- starters-starter-nzm-mccb- wiring-diagram.eps | |
| | eaton-manual-motor- starters-starter-msc-r- reversing-starter-wiring- diagram.eps | |
| | eaton-circuit-breaker-nzm- mccb-dimensions-020.eps | |
| 00 | eaton-circuit-breaker- switch-nzm-mccb- dimensions-016.eps | |
| | eaton-circuit-breaker- switch-nzm-mccb-3d- drawing-002.eps | |

| ASSEMBLIES | be evaluated. | |
|--|---|--|
| 10.4 CLEARANCES AND CREEPAGE DISTANCES | Meets the product standard's requirements. | |
| 10.5 PROTECTION AGAINST ELECTRIC SHOCK | Does not apply, since the entire switchgear needs to be evaluated. | |
| 10.6 INCORPORATION OF SWITCHING DEVICES AND COMPONENTS | Does not apply, since the entire switchgear needs to be evaluated. | |
| 10.7 INTERNAL ELECTRICAL CIRCUITS AND CONNECTIONS | ls the panel builder's responsibility. | |
| 10.8 CONNECTIONS FOR EXTERNAL CONDUCTORS | ls the panel builder's responsibility. | |
| 10.9.2 POWER- FREQUENCY ELECTRIC STRENGTH | ls the panel builder's responsibility. | |
| 10.9.3 IMPULSE WITHSTAND VOLTAGE | ls the panel builder's responsibility. | |
| 10.9.4 TESTING OF ENCLOSURES MADE OF INSULATING MATERIAL | ls the panel builder's responsibility. | |
| FITTED WITH: | Thermal protection | |
| POLLUTION DEGREE | 3 | |
| LIFESPAN, MECHANICAL | 15000 operations | |
| UTILIZATION CATEGORY | A (IEC/EN 60947-2) | |
| MOUNTING METHOD | Fixed Built-in device fixed built- in technique | |
| CLIMATIC PROOFING | Damp heat, constant, to IEC 60068-2-78 Damp heat, cyclic, to IEC 60068-2-30 | |
| EQUIPMENT HEAT DISSIPATION, CURRENT- DEPENDENT | 36.75 W | |
| ISOLATION | 300 V AC (between the auxiliary contacts) 500 V AC (between auxiliary contacts and main contacts) | |
| AMBIENT OPERATING TEMPERATURE - MAX | 70 °C | |
| AMBIENT OPERATING TEMPERATURE - MIN | -25 °C | |
| AMBIENT STORAGE TEMPERATURE - MAX | 70 °C | |
| AMBIENT STORAGE TEMPERATURE - MIN | 40 °C | |
| | | |

| | 100 |
|--|--|
| RATED INSULATION VOLTAGE (UI) | 1000 V |
| RATED OPERATING POWER AT AC-3, 230 V | 110 kW |
| RATED OPERATING POWER AT AC-3, 400 V | 200 kW |
| SWITCH OFF TECHNIQUE | Electronic |
| DEGREE OF PROTECTION | IP20 (basic degree of protection, in the operating controls area) IP20 |
| DIRECTION OF INCOMING SUPPLY | As required |
| ELECTRICAL CONNECTION TYPE OF MAIN CIRCUIT | Screw connection |
| OVERVOLTAGE CATEGORY | III |
| RATED OPERATIONAL CURRENT | 316 A (690 V AC-3) 349 A (400 V AC-3) |
| DEGREE OF PROTECTION (IP), FRONT SIDE | IP40 (with insulating surround) IP66 (with door coupling rotary handle) |
| DEGREE OF PROTECTION (TERMINATIONS) | IP10 (tunnel terminal) IP00 (terminations, phase isolator and strip terminal) |
| NUMBER OF POLES | Three-pole |
| TERMINAL CAPACITY (COPPER STRIP) | Min. 6 segments of 16 mm x 0.8 mm at box terminal 10 segments of 50 mm x 1 mm (2x) at rear-side width extension Max. 10 segments of 24 mm x 1 mm + 5 segments of 24 mm x 1 mm at box terminal Max. 10 segments of 32 mm x 1 mm + 5 segments of 32 mm x 1 mm at rear-side connection (punched) Max. 8 segments of 24 |
| | mm x 1 mm (2x) at box terminal Min. 6 segments of 16 mm x 0.8 mm at rear-side connection (punched) 3000 operations at 690 V |

| | AC-1 2000 operations at 690 V AC-3 2000 operations at 400 V AC-3 5000 operations at 400 V AC-1 |
|------------------|---|
| FUNCTIONS | Motor protection Phase failure sensitive |
| ТҮРЕ | Circuit breaker |
| SPECIAL FEATURES | IEC/EN 60947-4-1, IEC/EN 60947-2 The circuit-breaker fulfills all requirements for AC-3 switching category. R.m.s. value measurement and "thermal memory" Adjustable time delay setting to overcome current peaks tr at 6 x Ir also infinity (without overload releases) All AC-3 rating data applies to direct switching by the circuit-breaker under normal operating conditions. If, for example, a contactor takes over AC-3 switching under normal operating conditions, the full rated uninterrupted current applies to the circuit-breaker, In = Iu. Maximum back-up fuse, if the expected short-circuit currents at the installation location exceed the switching capacity of the circuit breaker (Rated short-circuit breaking capacity Icn) |

| | Rated current = rated uninterrupted current: 350 A Terminal capacity hint: Up to 240 mm² can be connected depending on the cable manufacturer. |
|--|---|
| APPLICATION | Use in unearthed supply systems at 690 V |
| SHOCK RESISTANCE | 20 g (half-sinusoidal shock 20 ms) |
| RATED OPERATIONAL CURRENT FOR SPECIFIED HEAT DISSIPATION (IN) | 350 A |
| RATED SHORT-TIME WITHSTAND CURRENT (T = 0.3 S) | 3.3 kA |
| RATED SHORT-TIME WITHSTAND CURRENT (T = 1 S) | 3.3 kA |
| SHORT-CIRCUIT RELEASE NON-DELAYED SETTING - MAX | 4900 A |
| SHORT-CIRCUIT RELEASE NON-DELAYED SETTING - MIN | 700 A |
| HANDLE TYPE | Rocker lever |
| INSTANTANEOUS CURRENT SETTING (II) - MAX | 4900 A |
| INSTANTANEOUS CURRENT SETTING (II) - MIN | 350 A |
| NUMBER OF OPERATIONS PER HOUR - MAX | 60 |
| OVERLOAD CURRENT SETTING (IR) - MAX | 350 A |
| OVERLOAD CURRENT SETTING (IR) - MIN | 175 A |
| RATED SHORT-CIRCUIT BREAKING CAPACITY ICS (IEC/EN 60947) AT 230 V, 50/60 HZ | 85 kA |
| RATED SHORT-CIRCUIT BREAKING CAPACITY ICS (IEC/EN 60947) AT 400/415 V, 50/60 HZ | 35 kA |

| RATED SHORT-CIRCUIT BREAKING CAPACITY ICS (IEC/EN 60947) AT 440 V, 50/60 HZ | 35 kA |
|--|---|
| RATED SHORT-CIRCUIT BREAKING CAPACITY ICS (IEC/EN 60947) AT 525 V, 50/60 HZ | 13 kA |
| RATED SHORT-CIRCUIT BREAKING CAPACITY ICS (IEC/EN 60947) AT 690 V, 50/60 HZ | 5 kA |
| STANDARD TERMINALS | Screw terminal |
| OPTIONAL TERMINALS | Box terminal. Connection on rear. Tunnel terminal |
| RELEASE SYSTEM | Electronic release |
| SHORT-CIRCUIT TOTAL BREAKTIME | < 10 ms |
| TERMINAL CAPACITY (ALUMINUM SOLID CONDUCTOR/CABLE) | 16 mm² (1x) at tunnel terminal 16 mm² (1x) direct at switch rear-side connection 10 mm² - 16 mm² (2x) direct at switch rear-side connection |
| TERMINAL CAPACITY (ALUMINUM STRANDED CONDUCTOR/CABLE) | 50 mm² - 240 mm² (1x) at 2-hole tunnel terminal 50 mm² - 240 mm² (2x) at 2-hole tunnel terminal 25 mm² - 185 mm² (1x) at tunnel terminal 25 mm² - 120 mm² (1x) direct at switch rear-side connection 25 mm² - 120 mm² (2x) direct at switch rear-side connection |
| TERMINAL CAPACITY (CONTROL CABLE) | 0.75 mm ² - 2.5 mm ² (1x) 0.75 mm ² - 1.5 mm ² (2x) |
| TERMINAL CAPACITY (COPPER BUSBAR) | M10 at rear-side screw connection Min. 20 mm x 5 mm direct at switch rear-side connection Max. 30 mm x 10 mm + 30 mm x 5 mm direct at switch rear-side connection Max. 10 mm x 50 mm (2x) at rear-side width extension |
| TERMINAL CAPACITY (COPPER SOLID CONDUCTOR/CABLE) | 16 mm² (2x) at box terminal 16 mm² (1x) direct at |

| | switch rear-side connection 16 mm² (2x) direct at switch rear-side connection 16 mm² (1x) at tunnel terminal 300 mm² (2x) at rear-side width extension |
|--|---|
| TERMINAL CAPACITY (COPPER STRANDED CONDUCTOR/CABLE) | 25 mm² - 120 mm² (2x) at box terminal 25 mm² - 240 mm² (1x) direct at switch rear-side connection 35 mm² - 240 mm² (1x) at box terminal 16 mm² - 185 mm² (1x) at 1-hole tunnel terminal 50 mm² - 240 mm² (2x) at 2-hole tunnel terminal 25 mm² - 240 mm² (2x) direct at switch rear-side connection |
| RATED SHORT-CIRCUIT BREAKING CAPACITY ICU (IEC/EN 60947) AT 400/415 V, 50/60 HZ | 35 kA |
| RATED SHORT-CIRCUIT MAKING CAPACITY ICM AT 400/415 V, 50/60 HZ | 105 kA |
| RATED SHORT-CIRCUIT MAKING CAPACITY ICM AT 440 V, 50/60 HZ | 74 kA |
| RATED SHORT-CIRCUIT MAKING CAPACITY ICM AT 525 V, 50/60 HZ | 53 kA |
| RATED SHORT-CIRCUIT MAKING CAPACITY ICM AT 690 V, 50/60 HZ | 40 kA |
| RATED SHORT-CIRCUIT MAKING CAPACITY ICM AT 240 V, 50/60 HZ | 187 kA |
| RATED IMPULSE WITHSTAND VOLTAGE (UIMP) AT AUXILIARY CONTACTS | 6000 V |
| RATED IMPULSE WITHSTAND VOLTAGE (UIMP) AT MAIN CONTACTS | 8000 V |

| 0000: | | |
|-------|--|--|
| 0000: | | |
| 000: | | |
| 00: | | |



□□□□ Eaton House 30 Pembroke Road Dublin 4, □□□ Eaton.com 







