



Eaton FH90

Eaton A200/B100 heater, Used with A200 Starter Sizes 4, 3-Phase Only, A200 Heater, NEMA, Ambient 102-110A, Non-Comp 92-99A, Used with A200 Starter Sizes 4, 3-Phase Only, Type A and B, Thermal and Fast Trip

□□□□

PRODUCT NAME	Eaton A200/B100 heater
CATALOG NUMBER	FH90
UPC	786678671147
PRODUCT LENGTH/DEPTH	2.3 in
PRODUCT HEIGHT	1.3 in
PRODUCT WIDTH	1.9 in
PRODUCT WEIGHT	0.07 lb
CERTIFICATIONS	UL Listed CSA Certified
CATALOG NOTES	Select heater coils based on full load current(FLA) shown on motor nameplate. Heater coils are rated to protect 40 degree C rise and a service factor of 1.15, Single-Phase requires 2 heaters, Three-Phase Requires 3 heaters

□□□□

SPECIAL FEATURES	Used with A200 Starter Sizes 4, 3-Phase Only
TYPE	A200 Heater
USED WITH	Used with A200 Starter Sizes 4, 3-Phase Only
DESIGN	NEMA
FULL LOAD CURRENT RANGE	Ambient 102-110 A, Non- Comp 92-99 A
OVERLOAD RELAY	Type A and B
TRIP TYPE	Thermal and fast trip

11

□□□□□	<u>Instructions for A200, A210, A250 size 6, two- or three-pole non-reversing or reversing motor controllers</u>
□□□□□□□	<u>Eaton Specification Sheet - FH90</u>

0000:	
0000:	
000:	
00:	



0000 Eaton House
 30 Pembroke Road
 Dublin 4, 0000
 Eaton.com

© 2026 〇〇 〇〇〇〇〇〇〇〇

